

Maximum Ratings:  
 Per output: 100 Watts  
 Controller total: 300 watts

### Setting Signal Timing

Press and hold the TIME-SET button until the time-set LED lights up, then release button. The controller will begin to cycle starting with the WALK step. When you want to advance to the next step, momentarily press and release the TIME-SET button (the controller will remember the duration for that step). Press and release button for the remaining steps.

After the last step in the sequence, the TIME-SET-LED light will turn off, and time setting is complete. The unit will then begin to cycle as normal with the new timing.

### Mounting Circuit Board

The plastic board holder should be mounted with double sided adhesive tape. Make sure mounting area surface is flat and pre-cleaned with rubbing alcohol.

This controller supports two versions of PED's :

#1> "DON'T WALK" where all text is red with separate incandescent lamps for DON'T and WALK.

#2> "DON'T WALK" (Red text) and "WALK" (Green text) with separate incandescent lamps for "DON'T WALK" and "WALK"



Use Yellow for WALK and Red for DON'T



Use Green for WALK and Red for DON'T WALK

